

CLICKFLASH G221HO

GENMAC



MADE IN ITALY

POWERED by
HONDA

Picture as a way of example only

MODEL	CLICKFLASH G221HO
GENERATING SET	
Alternator Type	Synchronous - three phase - compound regulated with brushes
Brand / Model	NSM WS 220 TDC
Voltage - Frequency	400V - 50 Hz - cos fi 0,8
PRP power	6,5 kVA 3PH
LTP power	7,2 kVA 3PH
Intensity PRP / LTP	9 / 10 A 1PH
Protection	IP 23
ENGINE	
Type	Single-Cylinder, 4 Strokes, air cooled, 3000 rpm, Start/Stop switch, Low Oil Pressure protection
Brand	HONDA
Model	GX390
Displacement - HP	389 cc - 11,7 HP
Fuel	Gasoline
Tank Capacity / Autonomy	6,1 lt / 2,9 h
Starting System	Recoil
Welder	
Operating Voltage	21,5 V - 28,8 V
Welding current	40A - 220A
Duty	220A - 35% / 170A - 60%
Control Panel	
	1x schuko 16A 230V; 1x CEE 16A 400V; Thermal breaker, Low Oil pressure protection
Dimensions mm L x l x H	780x540x560
Weight - Kgs.	90